

**LESSON 37 AN/FCC-100(V)7 & 9X EXAMINE EQUIRATE
AGGREGATE CDI 288 kbs CONFIGURATION**

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
1	Press the RESTART key.		
2	Press the NEXT ENTRY P key.	ACTIVATE	
3	Press the NEXT ENTRY P key. (Select EXAMINE using the DOWN ⤵ arrow key).	EXAMINE	EXAMINE
4	If selection displayed is not OFFLINE , then scroll through the options by pressing the NEXT ENTRY P key until OFFLINE is displayed. (Select OFFLINE using the DOWN ⤵ arrow key).	ACTIVE OFFLINE	OFFLINE
5	If selection displayed is not B-CONFIG , then scroll through the options by pressing the NEXT ENTRY P key until B-CONFIG is displayed. (Select B-CONFIG using the DOWN ⤵ arrow key).	A-CONFIG B-CONFIG	B-CONFIG
6	Select SYSTEM using the DOWN ⤵ arrow key.	SYSTEM CDI-EQUI	SYSTEM
7	Press the DOWN ⤵ arrow key.	288k AUX-NONE	
8	Press the DOWN ⤵ arrow key.	TRKREF-INT BUF63	
9	Press the DOWN ⤵ arrow key.	ERR-ENA REMHW-ENA	
10	Press the DOWN ⤵ arrow key.	CLLP-ACTIVE FRAME 2	
11	Press the DOWN ⤵ arrow key	NO-LOOPBACK	
12	Display of the B-CONFIGURATION is completed. Press the RESTART key.		

**LESSON 37 AN/FCC-100(V)7 & 9X EXAMINE EQUIRATE
AGGREGATE CDI 288 kbs CONFIGURATION**

**END OF THE FCC-100(V)7 & 9X SYSTEM EXAMINE
CONFIGURATION FOR CDI-EQU 288 KBS**